Description

[ELECTRICALLY ERASABLE PROGRAMMABLE READ ONLY MEMORY CELL AND PROGRAMMING METHOD THEREOF]

BACKGROUND OF INVENTION

[0001]   Field of Invention

[0002]   The present invention relates to a memory device and programming method thereof, and more particularly, to and Electrically Erasable and Programmable Read Only Memory (EEPROM) cell and programming method thereof.

[0003]   Description of the Related Art

[0004]   Electrically Erasable and Programmable Read Only Memory (EEPROM) serves for multiple data write/ read/ rapid erase operations, and the data stored therein stays after supplying power is off. Therefore, it is a versatile memory device that is broadly used in a personal computer and other electronic appliances.

[0005] A silicon nitride ROM is one of the common categories of EEPROM, whose structure is illustrated in *FIG. 1*. Referring to *FIG. 1*, the silicon nitride ROM comprises a stacking layer *108*, formed by silicon oxide tunneling dielectric layer *102*/ silicon nitride charge trapping layer *104*/ silicon oxide tunneling dielectric layer *106* sequentially, disposed on a substrate *100*, a gate conductive layer *110* over the stacking layer *108*, and source/ drain regions *112a* and *112b* disposed on two sides of the gate conductive layer *110* in the substrate *100*. Applying a bias configuration to the source/ drain region *112a* and the gate conductive layer *110* to program the EEPROM cell, where electronic charges in the substrate *100* are injected to the area *114* of the charge trapping layer *104* adjacent to the source/ drain region *112a* via Channel Hot Electron Injection (CHEI) effect, and a bit is stored therein.Jun042004Jun042004 Similarly, the above bias configuration can be applied to the source/ drain region *112b* and the gate conductive layer *110* for another programming operation, such that electronic charges in the substrate *100* are injected to an area *116* of the charge trapping layer *104* adjacent of the source/ drain region *112b* via CHEI effect, and another bit is stored therein. In other words, with programming oper-

ations in different directions, electronic charges are respectively stored on two sides of the charge trapping layer *104*, i.e. the silicon nitride EEPROM is a memory cell capable of two bits, namely 2 Bit/ Cell.

[0006] However, if a bit is already stored in the area *114* or *116*, when operating reverse read to the silicon nitride EEPROM cell, i.e. a reading direction is opposite to the programming direction, a 2^{nd}-bit effect might occur. That is, the stored bit increases the potential barrier. Therefore a threshold voltage V_t of reading operation is increased, and further limiting a sensing window between the threshold voltages of the two bits stored on two sides of the charge trapping layer.

[0007] Besides, if operating one-side reading to the silicon nitride EEPROM, then the V_t level of the bit adjacent to the source/ drain region *112b* in *FIG. 1* is affected.

[0008] Referring to *FIG. 2A*, it illustrates a transfer profile of the reading voltage and the threshold voltage level, where the horizontal axis represents reading voltage in volts, whereas the vertical axis represents threshold voltage level in volts. Moreover, the circle and square symbols in *FIG. 2A* respectively represent transfer profiles between the reading voltage and the threshold voltage for the right

hand side and left hand side of the charge trapping layer. According to *FIG. 2A*, since the source/ drain region on the right hand side is biased, a potential barrier of the bit stored on right hand side in the charge trapping layer is negatively affected, i.e. lowered, and thus an effective threshold voltage is lowered. Therefore, the threshold voltage level of the bit stored on right hand side in the charge trapping layer is lower than that of the bit stored on left hand side in the charge trapping layer.

[0009] Referring to *FIG. 2B*, which is similar to *FIG. 2A*, where a transfer profile between a reading voltage and a threshold voltage level is illustrated. What is different in *FIG. 2B* from *FIG. 2A* is an amount of electronic charges stored on two sides of the charge trapping layer, i.e. more electronic charges are stored in *FIG. 2B* than *FIG. 2A*. In *FIG. 2B*, more electrons are stored on two sides of the charge trapping layer, yet the effective threshold voltage is still affected by whether the adjacent source/ drain regions are biased with voltage. That is, the bit stored on right hand side of the charge trapping layer is affected by the source/ drain region with biased voltage on the right hand side, the effective threshold voltage is still lowered, which cannot be similar to that of the bit stored on left hand side of the

charge trapping layer.

SUMMARY OF INVENTION

[0010] In the light of the above descriptions, the present invention is directed to an Electrically Erasable and Programmable Read Only Memory (EEPROM) cell, which provides similar threshold voltage levels to the bitsin different charges stored on two sides of a charge trapping layer when performing read operation.

[0011] The present invention is also directed to a programming method of an EEPROM, for providing similar effective threshold voltage levels to the bits in different charges stored on two sides of a charge trapping layer when performing read operation.

[0012] According to one embodiment of the present invention, an EEPROM cell is provided, wherein the EEPROM cell comprises a stacking layer, a gate conductive layer, a source/ drain region, a second source/ drain region, a first pocket implant doping region and a second pocket implant doping region. The stacking layer is disposed over a substrate, and the stacking layer comprises a tunneling dielectric layer, a charge trapping layer and a block dielectric layer sequentially. The gate conductive layer is disposed over the stacking layer. The first source/ drain re-

gion and the second source/ drain region are respectively disposed on two sides of the gate conductive layer in the substrate. Moreover, the first pocket implant doping region is disposed below the stacking layer in the substrate being adjacent to the first source/ drain region, and the second pocket implant doping region is disposed below the stacking layer in the substrate being adjacent to the second source/ drain region, where a doping concentration of the first pocket implant doping region is different from a doping concentration of the second pocket implant doping region.

[0013] According to one embodiment of the present invention, a programming method is provided, which is suitable to an EEPROM cell. Wherein the EEPROM cell comprises a substrate, a charge trapping layer, a gate conductive layer, a first source/ drain region, a second source/ drain region, a first pocket implant doping region and a second pocket implant doping region, wherein a dopant concentration of the first pocket implant doping region is higher than a dopant concentration of the second pocket implant doping region. The programming method comprising applying a bias configuration to the gate conductive layer and the first source/ drain region for performing a first pro-

gramming, so as to inject electronic charges from the substrate to the charge trapping layer adjacent to the first source/ drain region. Moreover, applying the bias configuration to the gate conductive layer and the second source/ drain region for performing a second programming, so as to inject electronic charges from the substrate to the charge trapping layer adjacent to the second source/ drain region, wherein an amount of electronic charges injected during the first programming is larger than an amount of the electronic charges injected during the second programming.

[0014] Since the dopant concentration in the pocket implant doping regions are different, when programming the EEPROM cell, the electronic charges injected to two sides of the charge trapping layer are different, such that the threshold voltage of the bit stored adjacent to the first source/ drain region is higher. Therefore, when applying reading voltage to the first source/ drain region for reading from the EEPROM, the threshold voltage of the bit stored adjacent to the first source/ drain region can be lowered, whereas the threshold voltages of the bits stored on two sides are still similar.

BRIEF DESCRIPTION OF DRAWINGS

[0015] *FIG.*1is a schematic diagram of a cross-sectional view illustrating a conventional silicon nitride ROM cell.

[0016] *FIG. 2A* and *2B* are schematic transfer profile diagrams illustrating reading voltage vs. threshold voltage level of a conventional EEPROM cell.

[0017] *FIG. 3* is a schematic diagram of a cross-sectional view illustrating an EEPROM cell according to one embodiment the present invention.

[0018] *FIG. 4A* to *4D* are schematic diagrams of cross-sectional view illustrating an EEPROM cell under programming operation according to one embodiment of the present invention.

DETAILED DESCRIPTION

[0019] Referring to *FIG. 3*, it illustrates a schematic diagram of a cross-sectional view of an Electrically Erasable and Programmable Read Only Memory (EEPROM) cell according to one embodiment the present invention.

[0020] In *FIG. 3*, the EEPROM cell comprises a substrate *300*, a stacking layer *302*, a gate conductive layer *304*, source/drain regions *306a* and *306b*, pocket implant doing regions *308a* and *308b*.

[0021] Wherein the substrate *300* is exemplary a silicon substrate, which can be a P-type silicon substrate or an N-type sili-

con substrate. The stacking layer *302* is disposed over the substrate *300*, and the stacking layer *302* comprises a tunneling dielectric layer *310*, a charge trapping layer *312* and a blocking dielectric layer *314* sequentially. Wherein a material of the tunneling dielectric layer *310* is silicon oxide, for example, or other appropriate dielectric materials. A material of the charge trapping layer *312* is silicon nitride, for example, or other appropriate materials. A material of the blocking dielectric layer 314 is silicon oxide, for example, or other appropriate dielectric materials.

[0022] The gate conductive layer *305* is disposed over the stacking layer *302*, where a material of the gate conductive layer *304* comprises poly-silicon, doped poly-silicon or other appropriate conductive materials. The source/ drain regions *306a* and *306b* are disposed on two sides of the gate conductive layer*304* in the substrate *300*. Wherein a dopant type of the source/ drain regions *306a* and *306b* are N-type or P-type, for example, depending on the dopant type of the substrate.

[0023] Moreover, the pocket implant doping region *308a* is disposed below the stacking layer *302* in the substrate *300*, and is adjacent to the source/ drain region *306a*. The pocket implant doping region *308b* is disposed below the

stacking layer *302* in the substrate, and is adjacent to the source/ drain region *306b*.

[0024] It is noted that the doping concentration of the pocket implant doping region *308a* is different from (preferably higher than) that of the pocket implant doping region *308b*, i.e. an asymmetrical pocket implant region is formed. With this feature, when programming the EEPROM cell, more charges are stored in the part of the charge trapping layer *312* adjacent to the pocket implant doping region *308a*, and thus the threshold voltage of the bit stored in the region. Wherein different doping concentrations of the pocket implant doping regions *308a* and *308b* are rendered by different doses or different implant energy. Moreover, the dopant type of the pocket implant doping regions *308a* and *308b* is opposite to that of the source/ drain regions *306a* and *306b*, e.g. P–type or N–type dopant, which is subject to the dopant type of the source/ drain regions *306a* and *306b* in an embodiment of the present invention. When applying a voltage to the source/ drain regions *306a* or *306b*, a depletion region is formed in a PN junction between the source/ drain region *306a* (or *306b*) and the pocket implant doping region *308a* (or *308b*), where electric filed is strengthened, and electronic

charges are injected to the charge trapping layer *312* more easily.

[0025] The programming method of the EEPROM cell mentioned above is described hereinafter. Referring to *FIG. 4A*, a programming method of the EEPROM cell comprises performing a first programming step with applying a bias configuration to the gate conductive layer *304* and the source/drain region *306a*, where electronic charges in the substrate *300* are injected to an area *316* of the charge trapping layer *312* adjacent to the source/drain region *306a* via channel hot electron injection (CHEI) effect. To be more precise, a voltage level applied to the conductive layer *304* serves to turn on the channel region *320* between the source/drain regions *306a* and *306b*. When a bias potential between the source/drain regions *306a* and *306b* is substantially high, excess hot electrons are generated in the channel region *320* and part of which are injected through the tunneling dielectric layer *310* to the area *316* of the charge trapping layer *312* via the edge, and storing a bit therein. In an embodiment of the present invention, the bias configuration includes applying 10 volts to the conductive layer *304*, and applying 5 volts to the source/drain region *306a*, for example.

[0026] Thereinafter, operating temptempa second programming step, i.e. applying a same bias configuration of the conductive layer *304* and the source/ drain region *306b*, where electronic charges injected from the substrate *300* to an area *318* of the charge trapping layer *312* adjacent to the source/ drain region *306b* via channel hot electron injection (CHEI) effect, and stored as another bit therein. The foregoing programming steps are not arrange in a specific order, i.e. a bit can be stored in the are *318* then another bit is stored in the are *316*. Besides, electronic charges are stored in merely one of the areas *316* and *318* of the EEP-ROM cell according to an embodiment of the present invention (shown in *FIG. 4B* and *4C*), or stored in neither of the areas *316* nor *318* (shown in *FIG. 4D*), and thus a 2-bit, 4-level memory cell is formed.

[0027] It is noted that a dopant concentration of the pocket implant doping region *308a* is higher than that of the pocket implant doping region *308b*, thus an asymmetrical pocket implant doping region is formed. Therefore, an amount of electronic charges stored in the region *316* is higher than that stored in the region *318*, i.e. a threshold voltage of the region *316* is higher. Therefore, when applying a voltage to the source/ drain region *306a* for reading the EEP-

ROM cell, although an effective threshold voltage level of the region *316* can be lowered, the threshold voltage of the region *316* is still raised via the higher dopant concentration of the pocket implant doping region *308a*. Hence, when reading from the source drain region *306a*, the effective threshold voltage that is already lowered in the region *316* is similar to that of the region *318*.

[0028] Moreover, as opposed to increasing programming voltage or increasing programming time for raising threshold voltage of the region *316*, a same bias configuration is operated while different electronic charges are stored. Therefore, the programming method of the present invention is easier, and programming that is needed is shorter, as well as programming efficiency is improved.

[0029] Although the invention has been described with reference to a particular embodiment thereof, it will be apparent to those skilled in the art that modifications to the described embodiment may be made without departing from the spirit of the invention. Accordingly, the scope of the invention will be defined by the attached claims and not by the above detailed description.